

DX190 - 8 MM BENTLY™ COMPATIBLE PROXIMITY PROBE DRIVER FOR EDDY CURRENT PROBE, 4-20 MA RADIAL APPLICATIONS

DX190 - 8 mm Bently™-yhteensopiva kompakti pyörrevirta-anturi ohjain, 4-20 mA, Radial Applications

MSP_VIRTUEMA RT_MANUFACT URER	CTC
MSP_VIRTUEMA RT_SKU:	DX190
Sovellukset:	Liukulaakerin kunnonvalvonta
Herkkyys:	-7.87 V/mm
Tyyppi:	4-20 mA Radial
Halkaisija:	8 mm

Saatavana erilaisilla kokoonpanoilla, kaikki asiakastilauksen pohjalta:



www.facebook.com/mipelectronics



[www.linkedin.com/company/mip-electronics-ltd-/](https://www.linkedin.com/company/mip-electronics-ltd/)



www.youtube.com/channel/UCpKEF_7bS4dMC4qPokUAgDQ

Ordering Information

DX190 - - - -

Full Scale	System Length	Mounting Type	Regulatory Approval
04 = 0-4 mils pp	50 = 5.0 meter	00 = Panel (Mounting Screws Are Not Included)	00 = CE Certified
05 = 0-5 mils pp	90 = 9.0 meter	01 = DIN	
10 = 0-10 mils pp		02 = None	



Example Part Number: DX190-05-90-01-00
4140 Steel, 0-5 mils pp full scale, 9 meter system length, DIN mount, CE certified

MSP_VIRTUEMART_TechDETAILS

- Temperature Range: -31°F (-35°C) to 185°F (85°C)
- Linear Range: 10 to 90 mils (.25 - 2.30 mm) @ approximately -1 to -17 VDC
- Nominal Voltage Output: -200 mV/mil (-7.87 V/mm)
- 4-20 mA Output: defined by full scale selection
- Input Power/Voltage: 17.5 VDC to 30 VDC (Loop Powered)
- Aluminum enclosure
- Miniature 12-32 threaded connector
- 4 Position screw terminals + BNC output
- Calibrated to AISI 4140 steel

MSP_VIRTUEMART_PRODDOCS

1. [Esite](http://www.mip.fi/images/docs/fi/6_pro_dx190_ds.pdf), (URL: http://www.mip.fi/images/docs/fi/6_pro_dx190_ds.pdf)

MSP_VIRTUEMART_PRODUCT_IMAGE_TITLE



www.facebook.com/mipelectronics



www.linkedin.com/company/mip-electronics-ltd-/



www.youtube.com/channel/UCpKEF_7bS4dMC4qPokUAgDQ



www.facebook.com/mipelectronics



www.linkedin.com/company/mip-electronics-ltd/



www.youtube.com/channel/UCpKEF_7bS4dMC4qPokUAgDQ



www.facebook.com/mipelectronics



www.linkedin.com/company/mip-electronics-ltd-/



www.youtube.com/channel/UCpKEF_7bS4dMC4qPokUAgDQ